

XRC Joystick Adapter with Remote Switch

XRC Ethercon

1	W/Orange	VCC (5v)
2	Orange	Remote Switch
3	W/Green	Next
4	Blue	Stop
5	W/Blue	Prev
6	Green	Go
7	W/Brown	12v Remote
8	Brown	GND

XUSB-2 Joystick D-Sub

1		
2	Green	Go
3		
4	GND	GND
5	Brown	
6		
7	Blue	Stop
8	W/Orange	VCC (5v)
9		
10	W/Blue	Prev
11		
12		
13		
14	W/Green	Next
15		

Orange-Black Link to USB Remote pin 2
W/Brown Link to Audio 12v

XUSB-2 Remote 4pin

1	GND	USB GND
2	Black	USB Switch
3	GND	Audio GND
4	Black	Audio Switch

Red-Red Link Audio 12v

XDA1\XMAD1 Remote 4pin

1	GND	Audio GND
2	Black	Audio Switch
3	GND	12V GND
4	Red	12V